

# 2 Eyes Led Blinder Light

OL-B 2/200W



☞ KEYS INSTRUCTION



⊙  
MENU

⊙  
UP

⊙  
DOWN

⊙  
ENTER

## ☞ KEYS INSTRUCTION

Display	Function description
A001	Six channel address code, (001—512) B, C key to add and subtract address code values
CC00	color pulse with speed adjustment (00-99)
CP00	color fade with speed adjustment (00-99)
dE00	auto mode with speed adjustment (00-99)
bEbE	strobe by sound
Y000	Left lamp dimmer(000-255)
U000	right lamp dimmer(000-255)

## ☞ DMX MODE

Channel	Value	Function
Channel 1	1-255	dimmer
Channel 2	1-255	Left lamp dimmer
Channel 3	1-255	right lamp dimmer
Channel 4	0-255	strobe
Channel 5	0-255	micro function
Channel 6	0-255	function of speed, from slow to fast

## ☞ Technical Reference:

Voltage: AC110-220V 50-60HZ

Power: 200W

Light source: 2\*100w warm white cob

DMX Channels: 6 channel combination optional

GW: 4 KG/PCS