

LED Stage Lighting Operating Manual



OL-COB300WP

■ OUTDOOR



Please read manual carefully before use.

Thank you so much to choose this product; it is adopting the most advanced lamps, which is called LED lamps. It conquers a lot of disadvantages such as power wasting, short using life, high temperature, etc. It has advantages of power saving, long life (it can reach 60,000.00 hours in general circs), high brightness, fresh colors...It is the best stage illuminating and various effect decorative products.

DMX MODE

8 Channels Mode (A001)

CH	Function	Instruction
CH1	Total Dimmer	Total Dimmer- Dark to Bright
CH2	W1 Dimmer	W1 Dimmer- Dark to Bright
CH3	WW1 Dimmer	WW1 Dimmer- Dark to Bright
CH4	W2 Dimmer	W2 Dimmer- Dark to Bright
CH5	WW2 Dimmer	WW2 Dimmer- Dark to Bright
CH6	Total Strobe	Total Flash Strobe- Slow to Fast
CH7	Function Choice	000~050: CH1-CH6 Control. 051~100: Different Colors output 101~150: Colors Jump Change. 151~200: Colors Gradate. 201~250: Colors Pulse Change. 251~255: Sound-Active
CH8	Function/Speed	Slow to Fast (At the Colors output and sound choose the color)

4 Channels Mode (d001)

Ch	Function	Instruction
CH1	W1 Dimmer	W1 Dimmer- Dark to Bright
CH2	WW1 Dimmer	WW1 Dimmer- Dark to Bright
CH3	W2 Dimmer	W2 Dimmer- Dark to Bright
CH4	WW2 Dimmer	WW2 Dimmer- Dark to Bright

KEYS INSTRUCTION

**MENU****UP****DOWN****ENTER****DIGITAL SHOW FUNCTION FORM**

No	Show	Function	Value	Instruction
1	0001	DMX address	001-512	4CH mode
2	A001	DMX address	001-512	8CH mode
3	r252	W1 dim	000-255	UP,DOWN Change brightness
4	G255	WW1 dim	000-255	UP,DOWN Change brightness
5	b255	W2 dim	000-255	UP,DOWN Change brightness
6	u255	WW2 dim	000-255	UP,DOWN Change brightness
7	FH88	Strobe	01 - 88	UP,DOWN Change the speed
8	CL01	Colors chooe	01 - 08	UP,DOWN Change: color
9	CC99	Colors Jump	01 - 99	UP,DOWN Change the speed
10	DE99	Colors Gaddde	01 - 99	UP,DOWN Change the speed
11	CP99	Colors Pules	01 - 99	UP,DOWN Change the speed
12	SU01	Colors sound-Active	01-09	UP, DOWN Change the effects

Technical:

Voltage: AC110-220V 50-60HZ

Power: 300W

Light source: 4*75W COB

DMX Channels: 4/8 channel combination optional

IP:IP65

Operation: DMX512, Auto, Sound, Master-slave

