

LED Stage Lighting Operating Manual



OUTDOOR 7PCS LED PAR LIGHT

■ RGBWA+UV 6IN1



Please read manual carefully before use.

Thank you so much to choose this product; it is adopting the most advanced lamps, which is called LED lamps. It conquers a lot of disadvantages such as power wasting, short using life, high temperature, etc. It has advantages of power saving, long life (it can reach 60,000.00 hours in general circs), high brightness, fresh colors...It is the best stage illuminating and various effect decorative products.

☞ DMX MODE

10 Channels Mode (A001)

CH	Function	Instruction
CH1	Dimmer	R, G, B, W, Y, A dimmer : from dark to bright
CH2	R dimmer	R dimmer : from dark to bright
CH3	G dimmer	G dimmer : from dark to bright
CH4	B dimmer	B dimmer : from dark to bright
CH5	W dimmer	W dimmer: from dark to bright
CH6	Y dimmer	Y dimmer: from dark to bright
CH7	A dimmer	A dimmer: from dark to bright
CH8	Strobe	R, G, B, W , Y, Astrobe: slow to fast
CH9	Function choice	0~50: DMX 8CH Control. 51~100: Different Colors Output 101~150: Colors Jump Change. 151~200: Colors Gradate. 201~250: Colors Pulse Change. 251~255: Sound-Active
CH10	Function speed	Speed function, from slow to fast

6 Channels Mode (d001)

CH	Function	Instruction
CH1	R Dimmer	Red Dimmer- Dark to Bright
CH2	G Dimmer	Green Dimmer- Dark to Bright
CH3	B Dimmer	Blue Dimmer- Dark to Bright
CH4	W Dimmer	White Dimmer- Dark to Bright
CH5	Y Dimmer	Amber- Dark to Bright
CH6	P Dimmer	Ultraviolet- Dark to Bright

☞ KEYS INSTRUCTION



☞ DIGITAL SHOW FUNCTION FORM

No	Show	Function	Instruction
1	d001	DMX Address (1~512)	DMX-512 address set, 6 Channels mode
2	A001	DMX Address (1~512)	DMX-512 address set, 10 Channels mode
3	r255	Red (0~255)	UP, DOWN Change brightness
4	G255	Green (000~255)	UP, DOWN Change brightness
5	b255	Blue (000~255)	UP, DOWN Change brightness
6	U255	White (000~255)	UP, DOWN Change brightness
7	Y255	yellow (0~255)	UP, DOWN Change brightness
8	P255	Purple (0~255)	UP, DOWN Change brightness
9	FH99	Strobe flash (01~99)	UP, DOWN Change the speed
10	CL01	Different Colors Output (01~08)	UP, DOWN Change brightness
11	CC99	Colors Jump Change (01~99)	UP, DOWN Change the speed
12	DE99	Colors Gradate (01~99)	UP, DOWN Change the speed
13	CP99	Colors Pulse Change (01~99)	UP, DOWN Change the speed
14	SU01	Colors sound-Active (01~09)	UP, DOWN Change the effects

☞ Technical:

Voltage: AC90-240V 50/60HZ

Light source: 7PCS*12W RGBWA+UV 6IN1 LED

Color: Red, Green, Blue, White, Amber, Ultraviolet

Channel: 10CH/6CH

Operation: DMX512, Auto, Sound, Master-slave

IP:IP65

Size: 24*16*26cm

Weight: 3.5kg

