

Technical Reference:

Voltage: AC110-220V 50/60HZ

Power: 200w

Light source: 18 PCS*10W RGBW 4IN1 led

Material: Cast-Aluminum body

DMX Channels: 7 channel combination optional

N.W: 2.15kg

LED Stage Lighting Operating Manual

Digit PAR Light RGBW

■ Full color PAR

BX-342



CE

Please Read Over This Manual before Operating the Light Fixture

Thank you so much to choose this product; it is adopting the most advanced lamps, which is called LED lamps. It conquers a lot of disadvantages such as power wasting, short using life, high temperature, etc. It has advantages of power saving, long life (it can reach 60,000.00 hours in general circs), high brightness, fresh colors...It is the best stage illuminating and various effect decorative products.

Security:

1. Make sure the user voltage cannot higher or lower than the regulate value of the user manual.
2. Please take more attention while installing the fixtures. Avoid touching exposed AC cord, or will cause deadly accident.
3. When installing the fixtures, make sure the fixtures are not exposed in extremely hot, humid or dusty environment. Make sure the distance between the fixture and the lighted object is not less than 0.5 meter. Make sure there is no combustibile or explosive object around 0.5 meters.
4. Please operate the light fixture after becoming very familiar with the functions. In most cases, the light fixture will be broken by incorrect operation. It won't allow laypeople to operate this light.

DMX512 Control:

7 Channel Model

Channel	Channel data	Function instruction
CH1	0-255	Master dimming
CH2	0-255	Red dimming
CH3	0-255	Green dimming
CH4	0-255	Blue dimming
CH5	0-255	White dimming
CH6	1-255	Strobe control
CH7	1-255	Master function

