

6*1.5W LED Mini Bee-eye



Please read the instructions carefully before use

1-Skill Parameters

Voltage:AC100V-240V/50-60Hz

LEDs:6 x15W,RGBW 4 in 1 LEDs,

Power:100W

Lens degree standard:1.5°

Strobe:1-30T/sec electronic strobe and random strobe

Channel:Standard:11CH, Extend:14CH

Mode:DMX512,Auto,Sound,Mater/Slave

Product size:226*268*155mm

Carton Size:590x350x550mm (4 in 1)

N.W.:3.8KG

G.W.:4.5KG

2- Display Operation Instructions

DMX Set: Address	001-512	Address Setting
Channel Setting	11CH	11CH Channel
	14CH	14CH Channel
Show Mode	DMX Mode	DMX Control mode
	Fast Mode	Fast Running mode
	Slow Mode	Slow Running mode
	Scund Mode	Sound running mode
Sound Sense	0-99	Ser sitivity of sound control
Pan Inverse	OFF	Pan clockwise
	ON	pan anticlockwise
Tilt Inverse	OFF	Tilt clockwise
	ON	Tilt anticlockwise
While Balance	RED	0-255 Red balance adjust
	Green	0-255 Green balance adjust
	Blue	0-255 Blue balance adjust
	White	0-255 white balance adjust
Default Confirm	YES	System reset
Fixture Rest	YES	System reset

DMX Channel

11 CH	14 CH	Function	DMX address	Function
1	1	Pan	0-255	0-540°
	2	Pan fine	0-255	0-2.1°
2	3	Tilt	0-255	0-270°
	4	Tilt fine	0-255	0-1.0°
	5	Speed Control	0-255	From Slow to fast
3	6	Beam Effect	0-127	Location Skewing
			128-191	Clockwise Rotation
			192-255	Anticlockwise Rotation
			0-255	ZOOM
4	7	Main Dimmer	0-255	Main Dimmer 0-100%
5	8	R Dimmer	0-255	Red Dimmer 0-100%
6	9	G Dimmer	0-255	Green Dimmer 0-100%
7	10	B Dimmer	0-255	Blue Dimmer 0-100%
8	11	W Dimmer	0-255	White Dimmer 0-100%
9	12	Strobe	0-255	Speed from slow to fast
10	13	Color Change	0-10	Effect of other channels
			11-127	Color change
			128-160	Color jump
			161-200	Gradual change 1
			201-255	Gradual change 2
11	14	Color Change Speed	0-255	Speed Control, have function on 10/13Ch