

OL-COB200WB Cob Light



☞ KEYS INSTRUCTION



☞ DMX MODE

4CH

Channel	Function	Instruction
CH1	Dimmer	Dark to Bright
CH2	White Dimmer	White Dimmer- Dark to Bright
CH3	Warm White Dimmer	Warm White Dimmer- Dark to Bright
CH4	Strobe	Strobe- Slow to Fast

2CH

Channel	Function	Instruction
CH1	White Dimmer	White Dimmer- Dark to Bright
CH2	Warm White Dimmer	Warm White Dimmer- Dark to Bright

6CH

Channel	Function	Instruction
CH1	Dimmer	Dark to Bright
CH2	White Dimmer	White Dimmer- Dark to Bright
CH3	Warm White Dimmer	Warm White Dimmer- Dark to Bright
CH4	Strobe	Strobe- Slow to Fast
CH5	Function choice	Color change
CH6	Function speed	Speed function, from slow to fast

👉 DIGITAL SHOW FUNCTION FORM

No	Show	Function	Instruction
1	A001	DMX address	4CH mode (001~512)
2	d001	DMX address	2CH mode (001~512)
3	H001	DMX address	6CH mode (001~512)
4	CL01	Colors select	UP、DOWN Change brightness
5	CC15	Colors Jump	UP、DOWN Change brightness
6	DE15	Colors Gradate	UP、DOWN Change brightness
7	CP15	Colors Pulse	UP、DOWN Change brightness
8	U255	White dimmer	UP、DOWN Change brightness
9	C255	Warm white dimmer	UP、DOWN Change brightness
10	F255	Strobe	UP、DOWN Change brightness
11	SOND	Colors sound-Active	UP、DOWN Change brightness

👉 Technical Reference:

Voltage: AC110-220V 50-60HZ

Power: 200W

Light source: 200w white and warm white 2in1 cob

DMX Channels: 2/4/6 channel combination optional

GW: 6 KG/PCS