

Mini Wash7(4IN1)

User Handbook




(Suitable to 12W*7pcs LEDs)


Gerring to know the device

MINI WASH7

LEDs	7*12W/41NI
DMX Control	9/14Channel
Control Connections	3 Pin Female XLR sockets,3 Pin Male XLR sockets
Power Requirement	90V-240V, 50/60Hz
Power Consumption	60/90 Watts
Dimensions	225mm*225mm*270mm
Net Weight	4.2Kg



Control Panel



Control Connections

Color Options

The Unit offers a range of 16 preset colors. These can be individually selected with DMX control and feature in Auto Run and Sound Activated modes.

Color Options

The Unit offers a range of 16 preset colors. These can be individually selected with DMX control and feature in Auto Run and Sound

MINI WASH7

Manual control:

- Ch1 X-axis
- Ch2 Pan fine
- Ch3 Y-axis
- Ch4 Tilt fine
- Ch5
- Ch6 Light, Strobe
- Ch7 Red
- Ch8 Green
- Ch9 Blue
- Ch10 White
- Ch11 Color change
- Ch12 Color change-speed
- Ch13 programer

DMX512 Channels Control Illustration

Item	Channel
1	X-axis
2	Pan fine
3	Y-axis
4	Tilt fine
5	
6	Light, Strobe
7	Red
8	Green
9	Blue
10	White
11	Color change
12	Color change-speed