

# 288PCS Strobe Light User Manual

## OL-PIXEL RGB



### KEYS INSTRUCTION

No	Show	Function
1	A001	28channel
2	D001	7channel
3	C000	<p>C001 No effect , C002 Red,  C003 green, C004 blue,  C005 Red green, C006 Red blue,  C007 Green blue, C008 Red green blue,  C009 Gradual change, C010 Pulse change,  C011 Jump change,  C012 Effect 1,  C013 Effect 2  C014 Effect 3,  .....  C034 Effect 23  C035 The effect of integrated c012-c34  model  C036 sound control</p>

4	P000	Speed mode
5	R255	Manual red
6	G255	Manual green
7	B255	Manual blue
8	F000	Strobe speed

## DMX MODE

### 7 Channels Mode

Channel	Function	Instruction
CH1	Dimmer	Total dimmer
CH2	strobe	0-9 Strobe without effect 10-255 strobe from slow to fast
CH3	R dimmer	Red dimmer
CH4	G dimmer	Green dimmer
CH5	B dimmer	Blue dimmer
CH6	effect	Built-in mode 30-255
CH7	Effect speed	Built-in speed

## DMX MODE

### 28 Channels Mode

Channel	Function	Instruction
CH1	Dimmer	Total dimmer
CH2	strobe	0-9 Strobe without effect 10-255 strobe from slow to fast
CH3	Color select	0-29 Dimmer function 30-39 red 40-49 green

		50-59 blue 60-69 Red green 70-79 Green blue 80-89 Red blue 90-99 Red green blue 100-149 Pulse change 150-199 Gradual change 200-219 Combination effect of running horse
CH4	speed	Auto run speed, mainly plays a role in the 100-255 channel value function of CH3
CH5	Color 1	Red (first set of led bulb)
CH6	Color 2	Green (first set of led bulb)
CH7	Color 3	Blue (first set of led bulb)
CH8	Color 4	Red (second set of led bulb)
CH9	Color 5	Green (second set of led bulb)
CH10	Color 6	Blue (second set of led bulb)
CH11	Color 7	Red (third set of led bulb)
CH12	Color 8	Green (third set of led bulb)
CH13	Color 9	Blue (third set of led bulb)
CH14	Color 10	Red (fourth set of led bulb)
CH15	Color 11	Green (Group 4 led bulb)
CH16	Color 12	Blue (fourth set of led bulb)
CH17	Color 13	Red (Group 5 led bulb)
CH18	Color 14	Green (Group 5 led bulb)
CH19	Color 15	Blue (Group 5 led bulb)
CH20	Color 16	Red (Group 6 led bulb)
CH21	Color 17	Green (Group 6 led bulb)
CH22	Color 18	Blue (Group 6 led bulb)
CH23	Color 19	Red (Group 7 led bulb)
CH24	Color 20	Green (Group 7 led bulb)
CH25	Color 21	Blue (Group 7 led bulb)
CH26	Color 22	Red (Group 8 led bulb)
CH27	Color 23	Green (Group 8 led bulb)

CH28	Color 24	Green (Group 8 led bulb)
------	----------	--------------------------

### Technical Reference:

Voltage: 100 ~ 240V AC 50-60Hz

Light source: 288pcs 0.5w SMD RGB 3in1/ white led bulb

Control mode: Auto / master / slave / SOUND

Channel: 7CH/28CH

Net weight: 2.5kg

Product size: 28\*28\*27 cm