

LED Stage Lighting Operating Manual




OL-COB200-PRO



Please read manual carefully before use.

Thank you so much to choose this product; it is adopting the most advanced lamps, which is called LED lamps. It conquers a lot of disadvantages such as power wasting, short using life, high temperature, etc. It has advantages of power saving, long life (LED lamp it can reach 60,000.00 hours in general circs), high brightness, fresh colors...It is the best stage illuminating and various effect decorative products.

☞ Display interface



☞ DIGITAL SHOW FUNCTION FORM

| Display | Function description |
|---------|---|
| A001 | Six channel address code, (001—512) B, C key to add and subtract address code values |
| CC00 | color pulse with speed adjustment (00-99) |
| CP00 | color fade with speed adjustment (00-99) |
| dE00 | auto mode with speed adjustment (00-99) |
| bEbE | strobe by sound |
| Y000 | White dimmer(000-255) |
| U000 | Warm dimmer(000-255) |

☞ Channel mode

6CH

| Channel | Value | Function |
|-----------|-------|--------------|
| Channel 1 | 1-255 | dimmer |
| Channel 2 | 1-255 | white dimmer |

| | | |
|-----------|-------|--------------------------------------|
| Channel 3 | 1-255 | warm dimmer |
| Channel 4 | 0-255 | strobe |
| Channel 5 | 0-255 | micro function |
| Channel 6 | 0-255 | function of speed, from slow to fast |

Technical:

Voltage: AC110-220V 50-60HZ

Power: 200W

Light source: 200w warm white and white 2in1 cob

DMX Channels: 6 channel combination optional

GW: 6 KG/PCS

ONE
-PRO-